

Scan only

# HP ScanJet Enterprise Flow 5000 s4 Sheet-feed Scanner



Give your office powerful scan speed and accuracy. Built-in software and an 80-page automatic document feeder help you save time. Scan at up to 50 ppm/100 ipm.<sup>2</sup> Recommended for 6,000 pages per day.



## Fast, smooth scanning—even unattended

- Capture entire documents with one-pass duplex scanning up to 100 ipm
- Free up space for work. This HP ScanJet is small and slim—a modern design perfect for the desktop.
- Capture a wide range of documents—even stacks of mixed media sizes and types—with HP EveryPage.<sup>3</sup>
- Load up to 80 pages into the automatic document feeder for fast, unattended scanning.



## Peak workflow performance. Smarter scanning.

- Identify new devices and gain insight into scanning with HP Web Jetadmin remote discovery and monitoring.<sup>4</sup>
- Simplify the way you scan A3-size documents—no need for a carrier sheet.
- Scan images directly into applications with included and full-featured TWAIN and ISIS®.
- Easily transfer scans into editable text, encrypted PDF files, and more file types, using built-in OCR.



## Professional-grade scanning that helps save time

- Save time and simplify complex scan jobs with HP Smart Document Scan Software.
- Create one-button scan settings for recurring tasks, and make selections using the LCD control panel.
- Scan directly to mobile devices with the HP JetAdvantage Capture App, and then edit and save files.<sup>5</sup>
- Capture and organize documents, business cards, and other file types with feature-rich software.

<sup>1</sup> Scan speed measured at 300 dpi (black-and-white, grayscale, and color). Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.

<sup>2</sup> HP EveryPage is referred to as HP Precision Feed on HP ScanJet devices introduced prior to May 2013.

<sup>3</sup> HP Web Jetadmin is available for download at no additional charge at <http://www.hp.com/go/webjetadmin>

<sup>4</sup> Scanning from a mobile device requires the HP Wireless Adapter 100 (LZ761A), which must be purchased separately, and the HP JetAdvantage Capture App. The app is available for mobile devices running Android™ version 4.0 and higher, and can be downloaded from the Google Play™ store. For more information, see <http://www.hp.com/go/documentmanagement>. Wireless performance is dependent on physical environment and distance from access point and may be limited during active VPN connections. Wi-Fi Direct® scanning requires the mobile device to be connected directly to the Wi-Fi® network of the scanner. Wi-Fi and Wi-Fi Direct are registered trademarks of Wi-Fi Alliance®.

## Technical specifications

|   |  |
|---|--|
| <b>Scan Technology</b>                    | CMOS CIS   |
| <b>Scan Type</b>                          | Sheetfed; <b>Color Scanning:</b> Yes   |
| <b>Scan speed ADF (letter)</b>            | Up to 50 ppm/100 ipm for (b&w, 300ppi)   |
| <b>Task speed</b>                         | 10 x 15 cm (4 x 6 in) color photo to file (200 dpi, 24-bit, tiff): about 5.18 sec for single image scan; 10 x 15 cm (4 x 6 in) color photo to e-mail (150 dpi, 24-bit): about 4.98 sec for single image scan; about 1.43 sec for single image send to email. Totally 6.41 sec; A4 (8.27 x 11.69 in) PDF to e-mail (300 dpi, 24-bit): about 6.63 sec for single image scan; about 3 sec for single image send to email. Totally 9.63 sec                  |
| <b>Scan Resolution</b>                    | <b>Hardware:</b> Up to 600 dpi (color and mono, Sheet-feed)<br><b>Optical:</b> Up to 600 dpi (color and mono, Sheet-feed)  |
| <b>Scan Input Modes</b>                   | Two scan modes (simplex/duplex) on front-panel for HP SDS in Win OS and third parties applications via TWAIN, ISIS and WIA.  |
| <b>Scanner Advanced Features</b>          | Auto-color detect, auto-crop, auto-exposure, auto orient, OCR, edge removal, background cleanup, remove hole, color drop out, straighten the page, scan to cloud, scan to email, PDF security, misfeed detection advance setting, batch processing, barcode, scan to multiple desinations  |
| <b>ENERGY STAR Qualified</b>              | Yes  |
| <b>Output Resolution Dpi Settings</b>     | 75; 100; 150; 200; 240; 300; 400; 500; 600 ppi   |
| <b>Bit depth / Grayscale levels</b>       | 24-bits external 48-bits internal; <b>Grayscale Levels:</b> 256  |
| <b>Scan Size</b>                          | <b>ADF:</b> 216 x 3100 mm  |
| <b>Media Types</b>                        | Cut Sheet Paper, Printed Paper (Laser and ink), Pre-Punched Paper, Bank Checks, Business Cards, Freight Bills, Carbonless forms, Plastic Carrier sheets for easily damaged documents, Previously stapled media with staple removed   |
| <b>Media Size, ADF</b>                    | U.S.-Letter: 215.9 x 279.4 mm (8.5 x 11 in); U.S.-Legal: 215.9 x 355.6 mm (8.5 x 14 in); U.S.-Executive: 184.2 x 266.7 mm (7.25 x 10.5 in); ISO A4: 210 x 297 mm (8.3 x 11.7 in); JIS B5: 182 x 257 mm (7.2 x 10.1 in); ISO B5: 176 x 250 mm (7.0 x 9.9 in); ISO A5: 148 x 210 mm (5.8 x 8.3 in); ISO A6: 105 x 148 mm (5.8 x 4.1 in); ISO A7: 74 x 104 mm (2.9 x 4.1 in); ISO A8: 52 x 74 mm (2.0 x 2.9 in)   |
| <b>Media weight (ADF)</b>                 | 40 to 413 g/m <sup>2</sup>   |
| <b>Auto document feeder capacity</b>      | 80 sheets of 75 g/m <sup>2</sup> paper   |
| <b>Duty Cycle (Daily)</b>                 | Recommended for 6,000 pages  |
| <b>Standard connectivity</b>              | USB 2.0 and USB 3.0 (SuperSpeed)   |
| <b>Memory</b>                             | 512 MB   |
| <b>Processor Speed</b>                    | 550 MHz  |
| <b>Control Panel</b>                      | 2-line 16 character per line LCD display, Simplex button, Duplex button, Cancel button, Power button with a LED and Tool button  |
| <b>Image Scaling or Enlargement Range</b> | Will not perform any arbitrary scaling.  |
| <b>Twain Version</b>                      | TWAIN version 2.1  |
| <b>Software Included</b>                  | HP WIA scan driver, HP TWAIN scan driver, HP Smart Document Scan Software, HP Scanner Tools Utility, I.R.I.S. Readiris Pro, I.R.I.S. Cardiris, Nuance PaperPort, EMC ISIS driver   |
| <b>Compatible Operating Systems</b>       | Microsoft® Windows® 10, 8.1, 8, 7: 32-bit or 64-bit  |
| <b>Minimum System Requirements</b>        | <b>PC:</b> Microsoft® Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Microsoft® Internet Explorer  |
| <b>Operating environment</b>              | <b>Operating Humidity Range:</b> 15 to 80% RH (non-condensing)<br><b>Non-operating Humidity Range:</b> 0 to 90% RH (non-condensing)<br><b>Recommended Humidity Operating Range:</b> 15 to 80% RH (non-condensing)<br><b>Operating Temperature Range:</b> 10 to 35°C<br><b>Storage Temperature Range:</b> -40 to 60°C<br><b>Recommended Operating Temperature Range:</b> 10 to 35°C   |
| <b>Power</b>                              | <b>Power Supply Type:</b> External Power Adapter<br><b>Power Consumption:</b> 4.4 watts (ready), 0.8 watts (sleep), 0.1 watts (off), 0.1 watts (auto-off)<br><b>Power Requirements:</b> Input Voltage range: 90 - 264 VAC, Rated Frequency: 50 - 60Hz, Worldwide use   |
| <b>Dimensions (W x D x H)</b>             | 310 x 198 x 190 mm   |
| <b>Weight</b>                             | 3.8 kg   |
| <b>What's in the box</b>                  | HP ScanJet Enterprise Flow 5000 s4 Sheet-feed Scanner; Installation guide, Support flyer, Warranty guide; 2CDs; Power cord; USB cable; Power Adapter   |
| <b>Warranty</b>                           | 1 Year Limited Warranty (Return to HP/Dealer - Unit Exchange)  |
| <b>Electromagnetic emission standard</b>  | Class B Emissions; CISPR 22:2008 (International); European Union EMC Directive 2014/30/EU, EN 55022:2010 (CE mark); China GB9254-2008 (CCC); Taiwan CNS13438:2006 (BSMI); USA CFR47 Part 15, Subpart B (FCC); ICES-003:2012 Issue 6 (Canada); Australia C-tick (includes New Zealand); KN 22 and Korea KCC; EAC EMC Certificate; Ukraine EMC approval; EN 61000-3-2:2014 (harmonics); EN 61000-3-3:2013 (flicker); Immunity CISPR 24:2010, EN 50024:2010 |
| <b>Safety Approvals and Requirements</b>  | IEC 60950-1:2005 +A1+A11+A12 and all applicable amendments; CSA/UL 60950-1, 2nd edition (2007); EN 60950-1:2006 +A11 +A1 +A12+A2; EAC safety; Canada cUL CoC; China CCC; European Union CE; Kenya PVOC; Kuwait TER; Nigeria SON; Saudi Arabia SASO; South Africa NRCs; Taiwan BSMI; Ukraine safety approval  |
| <b>Accessories</b>                        | HP ScanJet Enterprise Flow 5000 s4/7000 s3 roller replacement kit L2756A   |

## Ordering Information

| Number | Description   |
|--------|---|
| L2755A | HP ScanJet Enterprise Flow 5000 s4 Sheet-feed Scanner |

### HP Care Packs

| Number | Description  |
|--------|--|
| UH369E | HP 3 year Return Scanjet 5000x Hardware Service                            |
| UH370E | HP 3 year Next business day Exchange ScanJet 5000x Hardware Service        |
| UH372E | HP 3 year Next business day Onsite Exchange ScanJet 5000x Hardware Service |

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to [hp.com/go/cpc](http://hp.com/go/cpc)

### HP Inc. offices

|             |                   |  |
|-------------|-------------------|--|
| Australia   | (613) 8833 5000   | <a href="http://hp.com.au">hp.com.au</a> |
| China       | (010) 6564 3888   | <a href="http://hp.com.cn">hp.com.cn</a> |
| Hong Kong   | (852) 3559 7777   | <a href="http://hp.com.hk">hp.com.hk</a> |
| India       | (80) 2612 9000    | <a href="http://hp.com/in">hp.com/in</a> |
| Indonesia   | (62-21) 5799 1088 | <a href="http://hp.com/id">hp.com/id</a> |
| Korea       | (02) 2199 0114    | <a href="http://hp.co.kr">hp.co.kr</a>   |
| Malaysia    | (603) 2332 3333   | <a href="http://hp.com.my">hp.com.my</a> |
| New Zealand | (09) 918 9555     | <a href="http://hp.co.nz">hp.co.nz</a>   |
| Philippines | (632) 888 5900    | <a href="http://hp.com/ph">hp.com/ph</a> |
| Singapore   | (65) 6275 3888    | <a href="http://hp.com.sg">hp.com.sg</a> |
| Taiwan      | (02) 8722 9000    | <a href="http://hp.com.tw">hp.com.tw</a> |
| Thailand    | (662) 353 9500    | <a href="http://hp.com/th">hp.com/th</a> |
| Vietnam     | (848) 3823 4151   | <a href="http://hp.com/vn">hp.com/vn</a> |

For the following countries, please fax your queries to (65) 6275 6707 Bangladesh, Bhutan, Brunei, Cambodia, Maldives, Nepal, Pakistan, Sri Lanka

### Supported paper

Contact HP via phone: Asia: 65 6253 8500

### Solutions

For more solutions information, please visit [hp.com/go/gsc](http://hp.com/go/gsc)



<sup>1</sup> With input and output trays folded and covers closed

<sup>2</sup> Power requirements are based on the country/region where the scanner is sold. Do not convert operating voltages. This will damage the scanner and void the product warranty.

<sup>3</sup> Actual speeds may vary depending on scan resolution, connectivity type, computer performance and application software.

To learn more, visit [hp.com](http://hp.com)

